

ALFATRON ALF-120W-UB 120W Mini Mixer Amplifier



DESCRIPTION

ALFATRON ALF – 120W-UB Mini Mixer Amplifier with MP3 Player, FM Radio and Bluetooth. It includes a remote controller.

FEATURES

- Compact public-address amplifier.
- Speaker output of 100V or 70V & 4 -16 ohms, rated power output of 120W.
- Built in Mp3 player, FM radio & Bluetooth with remote controller.
- 2 MIC inputs, 1 EMC input, 2 line inputs, 1 line output.
- Built in Class-D amplifier module and switching power, with 100V/70V transformer technology.
- Individual volume control for Mic 1-2, Aux 1-2, bass/treble and master volume control.
- Support both AC100-240V & DC 24V power supply.
- Priority: EMC > MIC1 > others.
- LED indicators for power, clip, protect and signal.
- With short-circuit, clip, overload and high temp protection.
- Ideal for small venues such as classrooms, retail stores, coffee shops, restaurants etc

TECHNICAL SPECIFICATIONS

Specification

Rated Power	: 120W
Speaker Outputs	: 100V or 70V & 4 Ohms - 8 Ohms – 16 Ohms
Connector	: Mic1 input by Unbalanced Jack Mic2 Balance XLR Socket Line 1-2 inputs by RCA: Line output by RCA
Attenuation	: Microphone 1-2, Line 1-2 and Mp3/FM, bass/treble and master
MIC1 – 3 input Sensitivity	: 5mV
AUX1 & 2 input Sensitivity	: 350mV
EMC input Sensitivity	: 350mV
MIC Frequency response	: 180Hz ~ 10kHz (+- 3dB)
AUX Frequency response	: 70Hz ~16Hz (+- 3dB)
Noise	: <5mV (4 Ohm load output terminal)
THD	: < 1% 1KHz
Protection	: Short Circuit, Clip Overload and high Temp protection
Treble adjustment	: 10dB (+-2)
Bass adjustment	: 10dB(+/-2)
Rated Power Supply	: AC~110-220V
Rated output voltage	: 60W/4 Ohm, AC220V
Priority	: EMC>MIC1>Others
Dimensions	: 247 x 198 x 66mm
Packaging Size	: 343 x 302 x 121mm
Net Weight	: 2.6Kg